



Model: ROBO III MS

Reliance walk through type of Metal Detector (**ROBO III MS Auto Set**) is designed to detect all types of metals (ferrous, nonferrous, ferrite). The search coil & control modules are housed in a aesthetically designed archway. The archway designed for guick installation & erection. Walk / Stop indicator is incorporated above the entrance of the archway to regulate the flow of traffic . All the controls & audio visual indication are provided on the top of the rear side of the archway. All electronic circuits are designed with plug-in card system for easier service ability.

Salient Features

- \Box For indoor use.
- Auto Set
- □ Micro Controller Based
- \Box LCD screen for messages.
- \Box Key pad for parameters settings.
- □ Ultra high sensitivity
- Equal sensitivity for ferrous & non-ferrous metal.
- □ No false alarm for external disturbances.
- □ Intelligent counter (IN /OUT/ NET)
- □ Mains/ Battery operated.
- □ In-built control unit & battery charger
- □ Multi-tone Audio/ Visual indication for detection.
- \Box Easy to install
- □ Detachable in three parts

Technical Specifications

Passage Clearance Floor Space Required : 0.4 sq.m Weight Power

: 760 x 510 x 1950 mm Overall arch assembly : 900 x 510 x 2140 mm. : Approx. 45 Kg. : 230 VAC <u>+</u>15% 50 Hz,50 VA & 12V Battery backup (In-built)

Sensitivity Control 1-9 level in steps

AN ISO 9001 : 2000 COMPANY

Low level 1-3

For security check purpose, object like fire arms, granade etc.

Optimum level 4-6

For higher security prone area. Small size of arms & ammunitions, LED's etc. THigh level 7-9

FOR anti-pilferage purpose, detects small objects (Ferrous/ Non-ferrous) size of 25 mm cube

тм

USED IN : Defence services, Police establishments, Factory watch & ward & Security services

TO KEEP PACE WITH LATEST TECHNOLOGY, " RELIANCE ELECTRONICS" RESERVES THE RIGHT TO UPDATE THE SYSTEM. HENCE SPECIFICATION ARE SUBJECT TO CHANGE

RELIANCE ELECTRONICS

Office : G-1, Hiranyamayee Soc., Opp. Hotel Natraj Nashik - Pune Road, NASHIK ROAD - 422101 Works : D -1/2, MIDC, Ambad, NASHIK - 422010 Tel: (W) +91-253-2384345/46,6513248 fax: +91-253 -2384347 Email : support@reliance-india.com, Web : www.reliance-india.com MANUFACTURER OF METAL DETECTORS, SECURITY EQUIPMENTS & ELECTRONIC INSTRUMENTS

